

1050 Heinz Avenue, Berkeley, California 94710 • (510) 848-4411 • www.alternativetechs.com

NEC SL2100 Telephone System User Guide

(SL2100 12-button phones with LINE keys)

MAKING OUTGOING CALLS

How to make an outgoing call:

- 1. Lift the handset
- 2. Dial 9
- 3. Dial number

How to call a previously dialed number:

- 1. Press **Redial** button
- 2. Use the arrows that appear on the soft keys to scroll to the number you want to call (or use arrows on directional pad)
- 3. Lift handset to call the displayed number

How to make a call using caller ID:

- 1. Press **List** soft key
- 2. Press **CID** soft kev
- 3. Use the arrows that appear on the soft keys to scroll to the number you want to call (or use arrows on directional pad)
- 4. Lift handset to call the displayed number

How to make a conference call:

- 1. Establish the first call
- 2. Press **CONF soft key** (1st soft key)
- 3. Establish the second call
- 4. Press **ADD soft key** (1st soft key) after second caller answers
- 5. Press **BEGIN soft key** (1st soft key) to establish three-way conference call —or—
- 5. Establish third call
- 6. Press **BEGIN soft key** (1st soft key) to establish four-way conference call

Phone System User Guide - 2 -

HANDLING INCOMING CALLS

How to answer an incoming call:

- 1. If the call is ringing at your extension, lift the handset
- —or—
- 1. If a call is ringing on another line or extension, lift handset and press the flashing key

How to put a call on HOLD (no one else can pick it up):

- 1. While on call, press **HOLD**
- 2. Hang up (OUT key flashes)
- 3. To retrieve the call, press blinking **OUT** key

How to put a call on PARK (so any other extension can pick it up):

- 1. While on call, press any available (unlit) **PARK** key
- 2. Hang up (PARK key flashes)

How to transfer a call to a co-worker:

- 1. While on call, press **Transfer**
- 2. Dial the co-worker's **extension number** or press the co-worker's **hotline** key
- 3. Announce call (optional)
- 4. Hang up (call will ring the co-worker's extension; if not answered, the call will automatically go to the co-worker's voicemail)

How to transfer a call directly to a co-worker's voicemail:

- 1. While on call, press **Transfer**
- 2. Press the **VMsg** soft key
- 3. Press the co-worker's **hotline** key or dial the co-worker's **extension number**
- 4. Hang up

How to use Do Not Disturb:

- 1. Press the **DND** button
- 2. Set the DND option:
 - -- Press 1 to block external calls
 - -- Press 2 to block intercom calls
 - -- Press 3 to block all calls
 - -- Press 4 to block transferred calls
 - -- Press 0 to cancel DND
- 3. Press **Speaker** to finish

INTERCOM FEATURES

How to intercom a co-worker:

- 1. Lift handset (optional)
- 2. Enter the **extension number**
- 3. Begin speaking after tones

Phone System User Guide - 3 -

How to intercom all extensions at once (paging):

- 1. Lift handset
- 2. Dial **7010**
- 3. Begin speaking after tones

How to set intercom calls to ring vs. go to speakerphone:

- 1. Press **Speaker** button
- 2. Dial **723** for signaling (ringing) or **721** for voice call (speakerphone)
- 3. Press **Speaker** to finish

PERSONALIZING YOUR EXTENSION

How to adjust the ring volume on your phone:

- 1. Press the **Speaker** button
- 2. Dial **729**
- 3. Press the top or bottom of the directional pad to adjust the volume to the desired level
- 4. Press **Speaker** to finish

How to change the ring tones on your phone:

- 1. Press the **Speaker** button
- 2. Dial **720**
- 3. Press 1 for intercom calls or 2 for outside calls
- 4. Press **1 through 8** to hear the 8 different ring tone choices
- 5. Press the number of your choice
- 6. Press **Speaker** to finish

How to forward your phone to an outside number or an extension:

- 1. Press the **Speaker** button
- 2. Dial **741**
- 3. Press 1 to set call forwarding
- 4. Enter the outside number (preceded by "9") or the 3-digit extension number
- 5. Press **Speaker** to finish

How to cancel call forwarding:

- 1. Press the **Speaker** button
- 2. Dial **741**
- 3. Press **0** to cancel call forwarding
- 4. Press **Speaker** to finish

How to program personal speed dial numbers (up to 10):

- 1. Press the **Speaker** button
- 2. Dial **755**
- 3. Press the key you want to program (1-9, 0 on the keypad)
- 4. Dial **9** and the telephone number (include 1 + area code for long distance)

Phone System User Guide - 4 -

- 5. Press **HOLD**
- 6. Enter name if desired (see diagram on page 4):

Use the keypad to enter letters, eg. Press 2 three times for the letter C

To delete a character, press the Feature key

To move forward, press the # key once; to make a space, press the # key twice

- 7. Press **HOLD**
- 8. Press **Speaker** to finish

—or—

- 7. Repeat steps 3 through 7 to program more speed dial numbers
- 8. Press **Speaker** to finish

How to view and dial personal speed dial numbers:

- 1. Press the **Dir soft key**
- 2. Press the **STA soft key**
- 3. Use the **soft key arrows** to scroll through personal speed dial numbers 1-10
- 4. Press the **Dial soft key** to dial the selected number

How to use shortcuts to personal speed dial numbers:

- 1. Lift the handset
- 2. Dial #7 then the key you programmed (1-9, and 0 to access speed dial #10)

How to program function keys for extensions or speed dial numbers:

- 1. Press the **Speaker** button
- 2. Dial **751**
- 3. Press an available function key
- 4. Dial **01**
- 5. Dial extension or 9+number for speed dial
- 6. Press **HOLD**
- 7. Press **Speaker** to finish

-or-

- 7. Repeat steps 3 to 6 to program more keys
- 8. Press **Speaker** to finish